

MEF EMC-FILTER 3-PHASE 1-STAGE



I:180A U:3x600 VAC book-style


Current: 180 A
1-stage

Attenuation curves on request.

[Link to Product](#)

Illustration





Product may differ from Image

Approvals



General data

Climatic category	25/085/21 (EN 60068-1)
Test isolation voltage	3.3 kV (L - N), 2 s; 3.1 kV (L -L), 2 s
Connection	Screw connection, touch protected
Mounting method	screw fixing
Dimensions H x W x D	380x120x170 mm

Technical Data

Connection cross section	25...95 mm ² single core (AWG 3...0000); 35...95 mm ² multiple core (AWG 2...0000)
--------------------------	--

Description

Functional description	The 3-phase and 1-/2-stage EMC filters MEF 3/1-3/2 are used in the range 0.1...30 MHz and dampen interferences found in cables from the mains, supply units and control systems. They are suitable for TN-C- and IT mains. The best results are obtained with s
------------------------	---

Commercial data

country of origin	IT
customs tariff number	85363090
minimum order quantity	1