

MEF EMC-FILTER 3-PHASE 2-STAGE



I:80A U:3x500 VAC book-style


Current: 80 A
2-stage

Attenuation curves on request.

[Link to Product](#)


Illustration





Product may differ from Image

Approvals



General data

Climatic category	25/085/21 (EN 60068-1)
Test isolation voltage	3.3 kV (L - N), 2 s; 3.1 kV (L - L), 2 s
Connection	Screw connection, touch protected
Mounting method	screw fixing
Dimensions H × W × D	295×70×177 mm

Technical Data

Connection cross section	0.5...25 mm ² single core (AWG 20...3); 0.5...16 mm ² multiple core (AWG 20...5)
--------------------------	--

Description

Functional description	The 3-phase and 1-/2-stage EMC filters MEF 3/1-3/2 are used in the range 0.1...30 MHz and dampen interferences found in cables from the mains, supply units and control systems. They are suitable for TN-C- and IT mains. The best results are obtained with s
------------------------	---

Commercial data

country of origin	IT
customs tariff number	85363030
minimum order quantity	1