## Fuse Blocks, Holders and Accessories





**Block Series:** 

**BH Series:** For use with Edison high speed semiconductor and "bolt-in" fuses

Base: Light weight, high temperature thermoplastic

Mounting Studs: Plated steel Nut: Plated steel

Washer: Spring steel Agency Approvals:

UL Recognized, Guide IZLT2/IZLT8, File E14853 up to 700V CSA, Class 6225-01, File 47235 up to 700V

Contact Edison Customer Satisfaction for ordering information and dimensional data.

## **Catalog Number BH Series**

Catalog Code Description: Block Series

Fuseblock Base

0 Small base for 0-200 amp fuses, 0-700V

1 Medium base, for 0-400 amp fuses, 0-2500V

2 Medium base, for 0-600 amp fuses, 0-5000V

3 Large base, for 0-700 amp, 0-1250V

Agency Approval

Wire Connector

- 0 No connector
- 1 1 Hole for #14 2/0 copper wire (for use with base 0)
- 2 2 Hole for #14 1/0 copper wire (for use with base 0)
- 3 2 Hole for #6 250 MCM copper wire (for use with base 1, 2, & 3)
- 4 2 Hole for #14 500 MCM copper cable (for use with base 3) See Note 1 below

Stud Size

- 1 ½ 20 (for use with bases 0, 1, & 2)
- $2\,\%_{16}$  18 (For use with bases 0, 1, & 2)
- 3 % 16 (for use with bases 0, 1, 2 & 3)
- 4  $\frac{7}{16}$  14 (for use with base 3) See Note 2 below.
- 5 % 16 (for use with base 3)

NOTES: 1. The #4 connector must be used with either the 7/16 - 14 or the 3/8" - 16 stud.

0 No agency approval

2 UL Recognition only

1 UL Recognition and CSA Certification

2. The only compatible connector for the 7/16" - 14 stud is #4.

3 cURus

- 3. Always check applicable end use standards for required spacing between blocks, fuses or other hardware.
- 4. For applications above 700V, consult appropriate electrical standard for proper creepage distances, clearance distances and insulator voltage withstand ratings.

## **Catalog Numbers**

BH-0122	BH-2001	BH-3004
BH-1001	BH-2002	BH-3033
BH-1002	BH-2003	BH-3144
BH-1003	BH-2031	BH-3145
BH-1131	BH-2032	_
BH-1132	BH-2033	_
BH-1133	BH-3003	_
	BH-0122 BH-1001 BH-1002 BH-1003 BH-1131 BH-1132	BH-0122 BH-2001 BH-1001 BH-2002 BH-1002 BH-2003 BH-1003 BH-2031 BH-1131 BH-2032 BH-1132 BH-2033