

## MODLINK MSDD DBL COMBI INSERT USA 2XNEMA 5-15

GFCI+2xRJ45 female/female + 1x3A fuse

2 × NEMA-GFCI 5-15 (screw terminals) 2 × RJ45, 8-pole metal, CAT5e (female/female) 1 × fuse (3 A)

## Link to Product

Illustration



Product may differ from Image

| Approvals                        |                    |
|----------------------------------|--------------------|
| c <b>FL</b> us                   |                    |
| General data                     |                    |
| Dimensions $H \times W \times D$ | 88×116×72 mm       |
| Communication inserts            |                    |
| Article number                   | 4000-68000-4120000 |
| Operating voltage                | max. 125 V AC      |
| Operating current                | max. 15 A          |
| Fuse                             | 3 A                |
| Connection                       | Screw terminals    |
| Mounting depth mounted           | approx. 70 mm      |
|                                  |                    |
| Commercial data                  |                    |

The information in this brochure has been compiled with the utmost care.

Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 05/16

Murrelektronik GmbH | Falkenstraße 3,71570 Oppenweiler | Fon +49 (71 91) 47-0, Fax +49 (71 91) 47-491000 | shop@murrelektronik.com | shop.murrelektronik.com



stay connected

| customs tariff number  | 85366990 |  |
|------------------------|----------|--|
| minimum order quantity | 1        |  |

The information in this brochure has been compiled with the utmost care. Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 05/16

Murrelektronik GmbH | Falkenstraße 3,71570 Oppenweiler | Fon +49 (71 91) 47-0, Fax +49 (71 91) 47-491000 | shop@murrelektronik.com | shop.murrelektronik.com