



Plug connectors and cables  
Plug connectors and cables / connecting cables  
with female connector

DOL-0J08-G0M5AA3



**Model Name** > [DOL-0J08-G0M5AA3](#)  
**Part No.** > [2046873](#)



#### Technical data

Accessory group:	Plug connectors and cables
Accessory family:	Connecting cables with female connector
Connection type head A:	Female connector, JST, 8-pin, straight
Connection type head B:	Cable
Cable diameter:	Ø 5.6 mm
Conductor cross-section:	4 x 2 x 0.15 mm <sup>2</sup>
Shielding:	Shielded
Bending radius:	> 7.5 x Leitungsdurchmesser im Schleppbetrieb, > 5 x Leitungsdurchmesser bei fester Verlegung
Status LED:	-
Special feature:	Drag chain use
Signal type:	Incremental
Items supplied:	JST including sealing
Cable:	0.5 m, 8-wire
Jacket material:	PUR, halogen-free
Jacket color:	Black

## PIN assignment

PIN	Signal TTL, HTL	Signal sine 1.0 V <sub>ss</sub>	Color of wires
1	$\bar{B}$	SIN-	Black
2	Not connected	Not connected	
3	Z	Z	Lilac
4	$\bar{Z}$	$\bar{Z}$	Yellow
5	A	COS+	White
6	$\bar{A}$	COS-	Brown
7	Not connected	Not connected	
8	B	SIN+	Pink
9	Not connected	Not connected	
10	GND	GND	Blue
11	Not connected	Not connected	
12	U <sub>s</sub>	U <sub>s</sub>	Red
Shield	Shield <sup>1)</sup>	Shield <sup>1)</sup>	

### Attention!

The flexible wires twisted in pairs must be assigned in accordance with the signals.

White/Brown = A/ $\bar{A}$  oder COS+/COS-  
 Lilac/Yellow = Z/ $\bar{Z}$   
 Pink/Black = B/ $\bar{B}$  oder SIN+/ SIN-  
 Red/Blue = preferably U<sub>s</sub> and GND

<sup>1)</sup> Shield connected to housing on side of encoder, connected to ground on side of control.

**Attention!** In combination with the electrical interfaces A, C, E and P only.

**Australia**

Phone +61 3 9457 0600  
1800 33 48 02 – tollfree  
E-Mail sales@sick.com.au

**Belgium/Luxembourg**

Phone +32 (0)2 466 55 66  
E-Mail info@sick.be

**Brasil**

Phone +55 11 3215-4900  
E-Mail marketing@sick.com.br

**Canada**

Phone +1 905 771 14 44  
E-Mail information@sick.com

**Česká republika**

Phone +420 2 57 91 18 50  
E-Mail sick@sick.cz

**China**

Phone +86 4000 121 000  
E-Mail info.china@sick.net.cn  
Phone +852-2153 6300  
E-Mail ghk@sick.com.hk

**Danmark**

Phone +45 45 82 64 00  
E-Mail sick@sick.dk

**Deutschland**

Phone +49 211 5301-301  
E-Mail info@sick.de

**España**

Phone +34 93 480 31 00  
E-Mail info@sick.es

**France**

Phone +33 1 64 62 35 00  
E-Mail info@sick.fr

**Great Britain**

Phone +44 (0)1727 831121  
E-Mail info@sick.co.uk

**India**

Phone +91-22-4033 8333  
E-Mail info@sick-india.com

**Israel**

Phone +972-4-6881000  
E-Mail info@sick-sensors.com

**Italia**

Phone +39 02 27 43 41  
E-Mail info@sick.it

**Japan**

Phone +81 (0)3 5309 2112  
E-Mail support@sick.jp

**Magyarország**

Phone +36 1 371 2680  
E-Mail office@sick.hu

**Nederland**

Phone +31 (0)30 229 25 44  
E-Mail info@sick.nl

**Norge**

Phone +47 67 81 50 00  
E-Mail sick@sick.no

**Österreich**

Phone +43 (0)22 36 62 28 8-0  
E-Mail office@sick.at

**Polska**

Phone +48 22 837 40 50  
E-Mail info@sick.pl

**România**

Phone +40 356 171 120  
E-Mail office@sick.ro

**Russia**

Phone +7-495-775-05-30  
E-Mail info@sick.ru

**Schweiz**

Phone +41 41 619 29 39  
E-Mail contact@sick.ch

**Singapore**

Phone +65 6744 3732  
E-Mail sales.gsg@sick.com

**Slovenija**

Phone +386 (0)1-47 69 990  
E-Mail office@sick.si

**South Africa**

Phone +27 11 472 3733  
E-Mail info@sickautomation.co.za

**South Korea**

Phone +82 2 786 6321/4  
E-Mail info@sickkorea.net

**Suomi**

Phone +358-9-25 15 800  
E-Mail sick@sick.fi

**Sverige**

Phone +46 10 110 10 00  
E-Mail info@sick.se

**Taiwan**

Phone +886 2 2375-6288  
E-Mail sales@sick.com.tw

**Türkiye**

Phone +90 (216) 528 50 00  
E-Mail info@sick.com.tr

**United Arab Emirates**

Phone +971 (0) 4 88 65 878  
E-Mail info@sick.ae

**USA/México**

Phone +1(952) 941-6780  
1 (800) 325-7425 – tollfree  
E-Mail info@sickusa.com

More representatives and agencies  
at [www.sick.com](http://www.sick.com)